Plugwise

Product information

Stealth

The Stealth is a specific product meant to be built in.
Consumers are not allowed to be handling this product independently. Building in the Stealth should always be executed by a registered installer.

INFORMATION FOR THE INSTALLER

Installation of the Stealth should be executed in conformity with the installation instructions as described in NEN 1010.

Observe carefully that the product is safely placed with regard to touch. It should be absolutely inaccessible for the user of the (living)space in which the product is installed. It is advised to install the product in its entirety into a casing of flame retardant material with strain relief.

When stripping the power cord in order to mount the Stealth in between, we recommend to keep the earth wire intact. If the earth wire has been interrupted after all it MUST be connected with the use of a welding clamp or a strip connector, which must be fitted firmly into the casing by the installer. The earth wire should never be connected to the screw connector of the Stealth!

Connect the phase wire of the connection to be switched to the L↑. Connect the 0-wire of the connection to be switched to one of the N-positions. Connect the phase wire of the incoming connection to the L. Connect the 0-wire to the still available N.

Voltage: 100-240 V~
Frequency: 50 / 60 Hz
Max current: 16 A
Dimensions: 57.1x39x21 mm
ZigBee Dynamic MESH 2.4 GHz

helpdesk@plugwise.com
+31(0) 252 43 30 70
www.plugwise.com

Be wise, plug in.